(Pages: 2)

Name....

Reg. No.....

## FOURTH SEMESTER B.TECH. (ENGINEERING) DEGREE EXAMINATION, JUNE 2011

EE 09 403/PTEE 09 402—SIGNALS AND SYSTEMS

(2009 admissions)

Time: Three Hours

Maximum: 70 Marks

## Part A

Answer all questions.

Each question carries 2 marks.

- 1. Sketch the function x(t) = u(t) 2u(t-2) + 3u(t-4) u(t-5).
- 2. When a discrete time system is BIBO stable.
- 3. Define poles and zeros of a transfer function.
- 4. What is meant by aliasing?
- 5. What are the properties of region of convergence?

 $(5 \times 2 = 10 \text{ marks})$ 

## Part B

Answer any four questions. Each question carries 5 marks.

- 1. Test whether the following system of equation represent LTI system :-
  - (i)  $y(t) = [\cos 3t]x(t)$ .

(2.5 marks)

(ii) y[n] = x[-n].

(2.5 marks)

2. What is the total energy DT signal x[n] which takes the values of unity at n = -1, 0 and 1?

efficient differential equation is given by dy(t)/dt+3

3. Plot pole-zero diagram of the following transfer functions:— of molecular land as to blamo (a)

(i) 
$$\frac{s+2}{s^2+2s+2}$$

(2.5 marks)

(ii) 
$$\frac{s+3}{s(s^2+4)(s+2)(s+1)}$$

(2.5 marks)

4. Find the DTFT of the following:-

$$x[n] = 13n - 2 - nu[-n-1).$$

5. State and prove convolution theorem of Z transform.

Turn over

(Pages : 2)

EXAMINATION, JUNE 2011

TURTH SEMESTER B.TECH.

the function x(t) = u(t) - 2u(t-2) + 3u(t-4) - u(t-4)

When a descrete time system is BIBO stable

6. Find the Laplace transform of the following:-

(i)  $x_1(t) = e^{-3t}u(t)$ .

(2.5 marks)

(ii)  $x_2(t) = \cos 4t u(t)$ .

(2.5 marks)

SMETRYS GUA SIANDIS-804 GO HATTYSOL OF HATAX AND SYSTEMS

## Part C

Answer any four questions. Each question carries 10 marks.

1. (a) Determine whether the following systems are static or dynamic, linear or non-linear, shift variant or invariant, causal or non-causal, stable or unstable:

Each question corries 2 morks

(i) y(t) = x(t+10) + x(t).

(5 marks)

(ii) dy(t)/dt + 10y(t) = x(t).

(5 marks)

0

(b) The input and output of a causal LTI system are related by the differential equation,  $\frac{d^2y(t)}{dt^2} + 6\frac{dy(t)}{dt} + 8y(t) = 2x(t)$ . Find the impulse response of the system.

2. (a) Consider a causal Discrete time LTI system whose input x[n] and output y[n] are related by the difference equation:  $y[n] - \frac{1}{4}y[n-1] = x[n]$ 

Find the Fourier series representation of output y[n] if  $x[n] = \sin(n 3\pi/4)$ .

1. Test whether the following system of equation in resent LTI system:

(b) Define Trigonometric Fourier series and derive the Fourier coefficients with example.

3. (a) State and prove properties of DTFS.

(5 marks)

(b) Write short notes on over sampling.

(5 marks)

What is the total energy DT signal x[n] which  $\gamma_0$  es the values of unity at n = -1, 0 and 1?

(c) Consider an LTI system for which the input x(t) and output y(t) satisfy the linear constant coefficient differential equation is given by dy(t)/dt + 3y(t) = x(t). Find the response h(t).

4. (a) Find the Z transform of the following:—

(i)  $x[n] = -a^n u[-n-1].$ 

(5 marks)

(ii)  $x[n] = 7(1/3)^n u[n] - 6(1/2)^n u[n]$ .

(5 marks

Or

(b) Define Z-transform and its properties.

mrelans if Z to mercent notation of  $4 \times 10 = 40$  marks

Find the DTFT of the following